

The 16 Channel Programmable Annunciator is a versatile audio-visual display panel. 12 and 24 Volt DC versions are available.

Each of its 16 switched negative input channels may be used for status indication or alternatively as an alarm which can be muted without affecting subsequent alarms.

In addition the colour of each LED is selectable as red, amber or green.

The annunciator may be located away from the generating set.



Pan 5

Standard Features

► Construction

Heavy duty sheet steel enclosure for wall mounting with removable front cover and removable gland plate.

Enclosure size 305 x 305 x 100 mm. The display printed circuit board, audible alarm and controls are mounted on the front cover.

The connection to the Printed Circuit Board, (P.C.B.) is via a plug-in type terminal bar thus facilitating easy termination of clients' interconnecting cables from the generating set panel. The front panel can be rotated through 90° or 180°.

► Controls

Lamp Test Push Button
Alarm Mute Push Button

► Colour Selection

Each channel is equipped with an LED which can potentially display one of three colours when activated. Selection is made by different combinations of its selector switch.

► Audible Alarm Selection

Each channel is equipped with a selector switch to select whether the alarm will sound when it is activated.



Optional Features

► Option PAN 6

Normal/Run Control Switch

► Option PAN 7

Lockdown Stop Push Button

Remote Annunciator



FG Wilson has manufacturing facilities in the following locations:

Northern Ireland • Brazil • China • India • USA

With headquarters in Northern Ireland, FG Wilson operates through a Global Dealer Network. To contact your local Sales Office please visit the FG Wilson website at www.FGWilson.com

